



Dimmer Compatibility Chart

ELL System

ELCO Lighting

For Reference Only

Testing conducted by ELCO Lighting is not a substitute for and does not imply certification by an independent laboratory or any other standards certification. Refer to manufacturer specifications for more detailed information on product certifications and standards. Consult the dimmer manufacturer prior to installation to ensure compatibility.

Manufacturer	Product	Part Number	Dimmed Light Output Range
Leviton	SureSlide® Electro-Mechanical Incandescent Slide Dimmer, 600W, 120 VAC 60Hz, Single-Pole	6631	8% - 100%
	SureSlide® 600W, 120 VAC 60Hz, SureSlide Preset Electro-Mechanical Incandescent Slide Dimmer	6633	9% - 100%
	Trimatron Deluxe 3-Way Electro-Mechanical Incandescent Rotary Dimmer with Push ON/OFF	6683-IW	9% - 100%
	IllumaTech Preset Electro-Mechanical, 600W, 120VAC 60Hz, Single-Pole & 3-Way Incandescent Slide Dimmer, LED Locator	IPI06-1LZ	8% - 100%
Lutron	Ariadni® 600W 3-Way Incandescent/Halogen Dimmer	AY-603P	8% - 100%
	Ariadni® C-L Single Pole/3-Way Dimmer. 150W Max for LED/CFL or 600W Incandescent/Halogen	AYCL-153P	5% - 100%
	Ariadni® 600W Single Pole, Magnetic Low Voltage Dimmer	AYLV-600P	7% - 100%
	Skylark Contour® Single Pole/3-Way Incandescent/Halogen or Magnetic Low Voltage, Preset Dimmer	CT-103P	6% - 100%
	Skylark Contour® C-L, Single Pole/3-Way Dimmer. 150W Max LED/CFL or 600W Incandescent/Halogen	CTCL-153P	5% - 100%
	Diva® Series Single Pole Dimmer	DV-600P	10% - 100%
	Diva® (gloss) 3-Way, Electronic Low Voltage Dimmer	DVELV-303P	5% - 100%
	Maestro® C-L Single Pole/3-Way/Multi-Location Dimmer. 150W Max for LED/CFL, or 600W Incandescent/Halogen	MACL-153M	3% - 100%
	Maestro® (Gloss) Single Pole/Multi-Location, Electronic Low Voltage Dimmer	MAELV-600	6% - 100%
	Skylark® Series 600W Single Pole	S-600P	10% - 100%
	Skylark® C-L Single Pole/3-Way Dimmer. 150W Max for LED/CFL or 600W Incandescent/Halogen	SCL-153P	5% - 100%
	Skylark® 300W, Single Pole, Electronic Low Voltage, Preset Dimmer	SELV-300P	4% - 100%

*NOTE: Refer to dimmer manufacturer's documentation for installation instructions and circuit details

Disclaimer: Minimum and maximum loads for LEDs and CFLs are given in number of lamps and may vary depending on the lamp being used. Testing conducted by ELCO Lighting is not a substitute for and does not imply certification by an independent laboratory or any other standards certification. Refer to manufacturer specifications for more detailed information on product certifications and standards.