ELCO Lighting

Project Name:

Fixture Type:

Date:

LOW VOLTAGE LED ANCHOR™ TRACK FIXTURE

LED or Halogen Lamp Fixtures · 3 finishes

Low Voltage Anchor™ Track Fixture for LED or Halogen MR16 BiPin Lamps.



FEATURES

- Metal housing.
- 90° vertical adjustment, 358° rotation.
- Use with ELCO 120V Single or Two Circuit Track.
- Lamp: 50W MAX, 12V GU5.3 MR16 LED or MR16 Halogen (not included).
- Lamp Holder: MR16 GU5.3.
- Driver/Transformer: 120V/12V/3W-50W Electronic AC, reverse phase dimmable.
- No minimum load transformer
- This track head comes standard as H Style. J (Juno) and L (Lightolier) styles are available: For J style please order PJTLO (W/B) with the track head. For L style please order PLTLO (W/B) with the track head. Note these must be factory installed.

DIMENSIONS



SPECIFICATIONS

Wattage	50W
Voltage	120V
Dimming	Triac

ITEM NUMBERS

ITEM NUMBER	WATTS	VOLTAGE	DIMMING	FINISH
ETLD530WW	50W	120V	Triac	White
ETLD530W	50W	120V	Triac	White with Black Baffle
ETLD530B	50W	120V	Triac	Black

FINISHES


White


White with Black Baffle


Black

Item page
elcolighting.com/items/low-voltage-led-anchor-track-fixture-0
Every item number, IES files, downloads and the latest revision.

PART OF THESE FAMILIES

MR16 GU5.3 Low Voltage Track Fixtures

↓ Dimmer compatibility list

elcolighting.com · LET-60 Transformer Dimmer List

© ELCO Lighting 2026. All rights reserved • Rev. 25 Sep 2026 • ELCO Lighting reserves the right to make specification and design changes without notice.

TECHNICAL DETAILS

Construction: Track fixture with a powder coated finish.

Adjustability: Track head is adjustable 180° vertically with 358° rotation.

Lamp: Compatible with GU5.3 MR16 LED or MR16 Halogen up to 50W. (Lamp not included).

Installation: Installs into H-Style track from ELCO or others. Compatible with Single and two circuit track. Can be special ordered as J-Style (requires PJTLO W/B) or L-Style (requires PLTLO W/B).

Electrical: Solid state electronic Low Voltage Transformer is compatible with LED and Non-LED 3W to 50W lamps. Designed for noiseless operation. Transformer is designed to be compatible with LED MR16 lamps to eliminate minimum load and flickering issues.

Dimmability: Works with 120V electronic low voltage rated dimmers. Dims down to 10%. For full list of dimmers, refer to the Dimmer Compatibility List.

Listings:

- ETL Listed
- RoHS Compliant

© ELCO Lighting 2026. All rights reserved • Rev. 25 Sep 2026 • ELCO Lighting reserves the right to make specification and design changes without notice.