ELCO Lighting

Project Name:

Fixture Type:

Date:

LOW VOLTAGE LED CYLINDER™ TRACK FIXTURE

LED or Halogen Lamp Fixtures · 6 finishes



FEATURES

- Metal housing.
- 90° vertical adjustment, 358° rotation.
- Use with ELCO 120V Single or Two Circuit Track.
- Lamp: 50W Max, 12V GU/GX5.3 MR16 LED or MR16 Halogen (not included).
- Lamp Holder: MR16 GU/GX5.3.
- Driver/Transformer: 120V/12V/3W-50W Electronic AC, reverse phase dimmable.
- This track head comes standard as H Style. J (Juno) and L (Lightolier) styles are available: For J style please order PJTLO (W/B) with the track head. For L style please order PLTLO (W/B) with the track head. Note these must be factory installed.

DIMENSIONS



SPECIFICATIONS

Wattage	50W
Voltage	120V
Dimming	Triac

FINISHES


Black


Bronze


White

Copper

Gold

Nickel

Item page
elcolighting.com/items/low-voltage-led-cylinder-track-fixture
Every item number, IES files, downloads and the latest revision.

PART OF THESE FAMILIES

MR16 GU5.3 Low Voltage Track Fixtures

⬇ Dimmer compatibility list

elcolighting.com · LET-60 Transformer Dimmer List

© ELCO Lighting 2026. All rights reserved • Rev. 25 Sep 2026 • ELCO Lighting reserves the right to make specification and design changes without notice.

ITEM NUMBERS

ITEM NUMBER	WATTS	VOLTAGE	DIMMING	FINISH
ETLD528B	50W	120V	Triac	Black
ETLD528BZ	50W	120V	Triac	Bronze
ETLD528W	50W	120V	Triac	White
ETLD528CP	50W	120V	Triac	Copper
ETLD528G	50W	120V	Triac	Gold
ETLD528N	50W	120V	Triac	Nickel

TECHNICAL DETAILS

Construction: Track fixture with a powder coated finish.

Adjustability: Track head is adjustable 180° vertically with 358° rotation.

Lamp: Compatible with BiPin GU5.3 LED and non-LED MR16 lamps up to 50W. (Lamp not included).

Installation: Installs into H-Style track from ELCO or others. Compatible with Single and two circuit track. Can be special ordered as J-Style (requires PJTLO W/B) or L-Style (requires PLTLO W/B).

Electrical: Solid state electronic Low Voltage Transformer is compatible with LED and non-LED 3W to 50W lamps. Designed for noiseless operation. Transformer is designed to be compatible with LED MR16 lamps to eliminate minimum load and flickering issues.

Dimmability: Works with 120V electronic low voltage rated dimmers. Dims down to 10%. For full list of dimmers, refer to the Dimmer Compatibility List.

Listings:

- ETL Listed
- RoHS Compliant

© ELCO Lighting 2026. All rights reserved • Rev. 25 Sep 2026 • ELCO Lighting reserves the right to make specification and design changes without notice.